



* Optional - connect to reset (TB1 R) if required.

AMD2 CONTROL

- ⊖ R — RESET
- ⊖ 1 — - 0 VDC
- ⊖ 2 — PARTIAL OPEN
- ⊖ 3 — EXIT
- ⊖ 4 — OFF
- ⊖ 5 — - 0 VDC
- ⊖ 6 — STOP IMPULSE
- ⊖ 7 — PRES. IMPULSE(1)
- ⊖ 8 — C-SWITCH, 0 VDC
- ⊖ 9 — PRES. IMPULSE(2)
- ⊖ 10 — + 18 VDC
- ⊖ 11 — - 0 VDC
- ⊖ 12 — OUTER IMPULSE
- ⊖ 13 — INNER IMPULSE
- ⊖ 14 — + 18 VDC
- ⊖ 15 — } LOCKING DEVICE
- ⊖ 16 — }

* 6 5 4 3 2 1
PS-6

* RECEIVER (A), EMITTER (A)
RECEIVER (B), EMITTER (B)
WH= WHITE, BL= BLACK



NOTE: 1) DO NOT CONNECT BROWN WIRES TO C-SWITCH COMMON.
2) OBSERVE POLARITY WITH BROWN CONNECTING TO GROUND (0 VDC).
3) A JUMPER MUST BE INSTALLED IN PINS 9,12 ON CONTROL BOX FOR RE-ENTRY SENSOR IN ONE-WAY TRAFFIC AS PER APPLICABLE ANSI STANDARD.

IF AFTER TROUBLESHOOTING A PROBLEM, A SATISFACTORY SOLUTION CANNOT BE ACHIEVED, PLEASE CALL B.E.A., INC. FOR FURTHER ASSISTANCE DURING EASTERN STANDARD TIME AT 1-800-523-2462 FROM 8AM - 5PM. FOR AFTER-HOURS, CALL EAST COAST: 1-866-836-1863 OR 1-800-407-4545 / MID-WEST: 1-888-308-8843 / WEST COAST: 1-888-419-2564. DO NOT LEAVE ANY PROBLEM UNRESOLVED. IF YOU MUST WAIT FOR THE FOLLOWING WORKDAY TO CALL B.E.A., LEAVE THE DOOR INOPERABLE UNTIL SATISFACTORY REPAIRS CAN BE MADE. NEVER SACRIFICE THE SAFE OPERATION OF THE AUTOMATIC DOOR OR GATE FOR AN INCOMPLETE SOLUTION.WEB: WWW.BEASENSORS.COM

BEA
We open up New Horizons
A HALMA GROUP COMPANY
100 ENTERPRISE DRIVE
PITTSBURGH, PA 15275
PHONE: (412) 249-4100
FAX: (412) 249-4101
EMAIL: www.beasensors.com

TITLE: BESAM CUD/J-9 AMD2 SLIDING DOOR WITH WIZARD II SYSTEM

SIZE: A	DRAWN BY: KJG	REV BY: KJG	PART NO: 80.0058.04
	SCALE: NONE	DATE: 13 JUL 2005	SHEET 1 OF 1